# **EXTREME GU1001CS**

60Hz@1800RPM 220/127V 3PH









### Picture for illustration purposes only

Overall performance	GU1001CS
PRP Continuous power kVA	909
PRP Continuous power kW	727
LTP Stand-by power kVA	1000
LTP stand-by power kW	800
Power factor cos fiq	0.8
Voltage VAC	220/127
Frequency Hz	60
Ampere PRP/LTP	2388 / 2627
Speed RPM	1800

### **Dimensions and noise level**

Length mm	5700
Width mm	2200
Height mm	3400
Net Weight kg	9550
Gross Weight kg	-
Sound pressure at 7 mt dBA	-

# **General features**

Silent generator with following specifications:

#### Frame:

- Heavy duty fabricated welded base plate with high quality steel UNI S235.JR
- Heavy duty, bell type, rubber anti-vibration mountings
- Fuel tank with drain plug and retention basin
- Oil draining mechanical pump

#### Canopy:

- Large doors for easy access for service and monitoring (maintenance)
   Electro-galvanized sheet DC01+ZE25/25 (EN 10152: 2009)
- High precision sheet cutting with nitrogen laser technology to avoid
- Weatherproof sealed joints
- Nylon hinges
- Lockable handles in each door
   "Orange peel" specific powder coat paint for outdoor usage white **RAI 9010**
- Rain cap on exhaust outlet
- Coolant refilling specific hatch
   Fuel filler outside enclosure
- Ecological Sound foam: 100% Recyclable, 40mm thickness, fire-proof self-extinguishing class1 fire-reaction compliant washable, mechanically fixed to the roof with zinc plated metal supports and to the doors with metal grid

### Muffler:

- Supersilent, Residential type
- With high heat paint coating

## **Control Panel:**

- Self-standing control panel tower made with metal structure easily removable for maintenance
- Easy access to control panel through a canopy's door, equipped with lexan window
- Control panel is divided in two independent and insulated boxes separating Controls (Controller and numbered terminal board) from Power connection (circuit breaker and cable inlet)
- External dedicated area to make easier the electrical connection to the
- Power connection between circuit breaker and alternator made with high resistance cables and using cable glands for waterproof connections

All units and components are prototype tested, factory build and production tested. A specific control procedure during the several stages of production ensures long life and reliability.

## Data reference

Standard reference conditions temperature 25°C, altitude 1-1000m asl, relative humidity 30%, atmospheric pressure 100 kPa (1 bar), power factor 0.8 lag, balanced load - non distortional. Fuel consumption is nominal and refers to specific weight 0.850 gr/lt. Power performance data as quoted can be obtained after the initial running-in period of the engine, during which one has to follow the instructions of the engine manufacturer as stated in the use and maintenance manual of the specific engine. The tolerance shown by the engine manufacturer is +/- 5%. Sound power values refer to free field conditions: the installation site may influence the values. Dimensions, weights and other specifications contained in the technical data sheet and related attachments are nominal, subject to tolerances and refer to the model with standard equipment; any optional and additional equipment/accessories can modify weight, dimensions, performance.P.R.P. Prime Power-Continuous power at variable load: The power that a genset can supply in continuous service at a variable load for an unlimited applicable overload must be less than the percentages stated by the Manufacturer.L.T.P. Limited-time running power-Limited power: The maximum power that a genset can supply for a limited time respecting the maintenance intervals established in the environmental conditions stated by the Manufacturer according to ISO 8528-1. The number of hours per year is stated by the Manufacturer. Overload is not permitted. For reasons of transport and/or storage, liquids (oil and antifreeze) and batteries might not be included in the delivery.





# **EXTREME GU1001CS**

60Hz@1800RPM 220/127V 3PH



## **Engine general data**

Engine brand	Cummins
Model	QSK23-G3
PRP Power kW	809.00
LTP Power kW	895.00
Fuel	Diesel
Nr. cylinders	6
Air intake	Turbo intercooler
Cooling	Water
Cubic capacity I.	23.10
Speed regulation	Electronic
Performance Class - steady state regulator accuracy +/- %	G3 - 0.25
Load Step G1 - KWe	-
Load Step G2 - KWe	-
Load Step G3 - KWe	-
Voltage VDC	24
Emissions	-

# Alternator general data

Alternator brand	Stamford
Model	S6L1D-C
Type of excitation	Separate excitation
Type of regulation	AVR
Regulator precision +/-%	0.50
Churchine dete	

## Structure data

Tank capacity I. 400 Retention basin yes	Type of structure	EXTREME
Retention basin yes	Tank capacity I.	400
	Retention basin	yes
Exhaust diameter mm 168	Exhaust diameter mm	168

# **Fuel consumption**

Consumption 25% I./h	56.00
Consumption 50% I./h	97.00
Consumption 75% I./h	139.00
Consumption 100% I./h	189.00
Autonomy at 75% of load h.	≈ 3 h

# **Engine liquids and equipment**

Type of lubricant	Oil SAE 15W40
Lubrication capacity I.*	74.00
Type of coolant	Antifreeze liquid
Coolant capacity I.*	156.50
Air intake filter	Paper cartridge
Battery capacity Ah	50 Ah Optima
Number of batteries*	2

# Fuel system and energy balance

AC pump suction head kPa	-
Combustion air flow volume LTP m3/min	67.90
Cooling air capacity LTP m3/min	996.00
Exhaust gas flow-density LTP m3/min	183.40
Exhaust gas temperature LTP °C	514.00
Brake mean effective pressure kPa	10.20
Energy to exhaust LTP kWt	569.00
Energy to coolant LTP kWt	235.00
Energy to radiation LTP kWt	76.00

# **Control panel features**

# QTVA-7320

Self-standing tower with metal box

Circuit breaker

AMF controller DSE7320

- Voltmeter, Frequencymeter, Ammeter
   Generator power (kW, kV Ar, kV A & pf) monitoring
- Hour meter
- Fuel level meter
- Overload (kW & kV Ar) protection
- Low oil pressure protection
- High coolant temperature protection
- Low fuel level protection
- Battery charger alternator fault

- Rpm protection Emergency stop button Audible alarm

Terminal board for ATS connection

RS232 & RS485 Port

Can Bus reading Port (if standard on the engine)

Battery charger

On/off switch



Dealer



