# **STRONG-RENT G45YS-M5**

## 50Hz@1500RPM 400/230V 3PH





### Picture for illustration purposes only

PRP Continuous power kVA45PRP Continuous power kW36LTP Stand-by power kVA49LTP stand-by power kW39Power factor cos fip0.8Voltage VAC400/230Frequency Hz50Ampere PRP/LTP65 / 70	Overall performance	G45YS-M5
LTP Stand-by power kVA 49 LTP stand-by power kW 39 Power factor cos fiφ 0.8 Voltage VAC 400/230 Frequency Hz 50	PRP Continuous power kVA	45
LTP stand-by power kW 39 Power factor cos fip 0.8 Voltage VAC 400/230 Frequency Hz 50	PRP Continuous power kW	36
Power factor cos fiφ   0.8     Voltage VAC   400/230     Frequency Hz   50	LTP Stand-by power kVA	49
Voltage VAC   400/230     Frequency Hz   50	LTP stand-by power kW	39
Frequency Hz 50	Power factor cos fiq	0.8
	Voltage VAC	400/230
Ampere PRP/LTP 65 / 70	Frequency Hz	50
	Ampere PRP/LTP	65 / <b>70</b>
Speed RPM 1500	Speed RPM	1500

## Dimensions and noise level

Length mm	2220
Width mm	960
Height mm	1263
Net Weight kg	1035
Gross Weight kg	-
Sound pressure at 7 mt dBA	65.00

### Data reference

Standard reference conditions temperature 25°C, altitude 1-1000m asl, relative humidity 30%, atmospheric pressure 100 kPa (1 bar), power factor 0.8 lag, balanced load - non distortional. Fuel consumption is nominal and refers to specific weight 0.850 gr/lt. Power performance data as quoted can be obtained after the initial running-in period of the engine, during which one has to follow the instructions of the engine manufacturer as stated in the use and maintenance manual of the specific engine. The tolerance shown by the engine manufacturer is +/- 5%. Sound power values refer to free field conditions: the installation site may influence the values. Dimensions, weights and other specifications contained in the technical data sheet and related attachments are nominal, subject to tolerances and refer to the model with standard equipment; any optional and additional equipment/accessories can modify weight, dimensions, performance.P.R.P. Prime Power-Continuous power at variable load: The power that a genset can supply in continuous service at a variable load for an unlimited applicable overload must be less than the percentages stated by the Manufacturer.L.T.P. Limited-time running power-Limited power: The maximum power that a genset can supply for a limited time respecting the maintenance intervals established in the environmental conditions stated by the Manufacturer according to ISO 8528-1. The number of hours per year is stated by the Manufacturer. Overload is not permitted.\*For reasons of transport and/or storage, liquids (oil and antifreeze) and batteries might not be included in the delivery.



## **General features**

Silent Generator specifically designed for mobile application and Rental. Easy to use and handle.

Mounting last generation of engine with low emission, for a clean power.

### Frame:

- Heavy duty fabricated welded base plate with high quality steel UNI S235 JR

- Heavy duty, bell type, rubber anti-vibration mountings
- Fuel tank with drain plug and retention basin - Oil draining mechanical pump
- Base with bilateral forklift pockets allow lifting from all sides

### Canopy:

Four large doors for easy access for service and maintenance
 Electro-galvanized sheet DC01+ZE25/25 (EN 10152: 2009)

- High precision sheet cutting with nitrogen laser technology to avoid oxidation
- Sandblasting and cataphoresis treatment of intake / exhaust grids
- Weatherproof sealed joints
- Lockable handles in each door
- RAL 9010 "orange peel" specific powder coat paint for outdoor usage
- Rain cap on exhaust outlet
- Coolant refilling specific hatch
- Fuel filler outside enclosure
- Central lifting hook

- Ecological Šound foam: 100% Recyclable, 35mm thickness, fire-proof self-extinguishing class1 fire-reaction compliant washable, mechanically fixed to the frame

#### Muffler

- Supersilent, Residential type, integrated in the canopy

- Exhaust manifold insulation jacket

- With aluminum coating

### **Control Panel:**

- Metal Control panel with protective back cover

- Dedicated area to make easier the electrical connection to the load

All units and components are prototype tested, factory build and production tested. A specific control procedure during the several stages of production ensures long life and reliability.

Page

# **STRONG-RENT G45YS-M5**

# 50Hz@1500RPM 400/230V 3PH



## Engine general data

Engine brand	Yanmar
Model	4TNV98CT-IYE
PRP Power kW	35.00
LTP Power kW	43.70
Fuel	Diesel
Nr. cylinders	4
Air intake	Turbocharged
Cooling	Water
Cubic capacity I.	3.32
Speed regulation	Electronic
Performance Class - steady state regulator accuracy +/- %	G3 - 1.00
Load Step G1 - KWe	-
Load Step G2 - KWe	-
Load Step G3 - KWe	-
Voltage VDC	12
Emissions	Euro stage 5

### Alternator general data

Alternator brand	Mecc-Alte
Model	ECP32-2S/4C
Type of excitation	Self-excited
Type of regulation	AVR
Regulator precision +/-%	1.00
Structure data	
Type of structure	STRONG-RENT
Tank capacity I.	100
Retention basin	yes
Exhaust diameter mm	50

# **Fuel consumption**

Consumption 25% I./h	3.40
Consumption 50% I./h	5.60
Consumption 75% I./h	8.30
Consumption 100% I./h	11.00
Autonomy at 75% of load h.	≈ 12 h

## Engine liquids and equipment

Type of lubricant	Oil SAE 5W40 Low SAPS CJ4
Lubrication capacity I.*	11.20
Type of coolant	Antifreeze liquid
Coolant capacity I.*	8.00
Air intake filter	Paper cartridge
Battery capacity Ah	100
Number of batteries*	1

## Fuel system and energy balance

AC pump suction head kPa	-
Combustion air flow volume LTP m3/min	-
Cooling air capacity LTP m3/min	-
Exhaust gas flow-density LTP m3/min	-
Exhaust gas temperature LTP °C	-
Brake mean effective pressure kPa	-
Energy to exhaust LTP kWt	-
Energy to coolant LTP kWt	-
Energy to radiation LTP kWt	-

# **Control panel features**

## QFIP-AMF25-RENT-PT3

No. 1 CEE 63A 400V No. 1 CEE 32A 400V No. 1 CEE 32A 400V Thermal breaker Circuit breaker Controller Comap AMF25 - Voltmeter, Frequencymeter, Ammeter - Generator power (kW, kV Ar, kV A & pf) monitoring - Hour meter - Fuel level meter - Overload (kW & kV Ar) protection - Low oil pressure protection - High coolant temperature protection - Low fuel level protection

- Battery charger alternator fault
- Rpm protection

- Oil pressure and engine temperature reading

Analogic fuel level instrument

Emergency stop button Quick connector for remote start/ATS

On/off switch



Dealer



© 2017 GENMAC - P.I./VAT IT 01224860351 - cap. soc. € 100.000,00 i.v. / R.E.A. RE n.170570 - Reg. Imp. RE n.01524820402 2 of 2 Export M/RE012315 - GENMAC S.r.I.s.u. is subject to management and coordination of IPG SpA - Milano, Via Jae: Messantia Asion: 00-28/02/22 Reg. Imp. n.12616930967