## **DIAMOND RGU375PS**

60Hz@1800RPM 440/254V 3PH









Picture for illustration purposes only

Overall performance	RGU375PS
PRP Continuous power kVA	338
PRP Continuous power kW	270
LTP Stand-by power kVA	375
LTP stand-by power kW	300
Power factor cos fiφ	0.8
Voltage VAC	440/254
Frequency Hz	60
Ampere PRP/LTP	444 / 493
Speed RPM	1800

#### Dimensions and noise level

Length mm	4270
Width mm	1350
Height mm	2370
Net Weight kg	3370
Gross Weight kg	-
Sound pressure at 7 mt dBA	-

## **General features**

Silent generator with following specifications:

#### Frame:

- Heavy duty fabricated welded base plate with high quality steel UNI S235 JR
- Heavy duty, bell type, rubber anti-vibration mountings
- Dedicated area to make easier the electrical connection to the load
- Fuel tank with drain plug and retention basin
- Oil draining mechanical pump
  Robust skid base with 4 towing eyes

#### Canopy:

- Large doors for easy access for service and maintenance
- Electro-galvanized sheet DC01+ZE25/25 (EN 10152: 2009)
- Weatherproof sealed joints
- High-tech Nylon hinges: rust-free, no need to lubricate
- Lockable handles in each door
- Windproof door stop
- White RAL 9010 "orange peel" specific powder coat paint for outdoor usage
- Rain cap on exhaust outlet
- Coolant refilling specific hatch
  Fuel filler outside enclosure
- Fuel tank cap with lock
- Ecological Sound foam: 100% Recyclable, 40mm thickness, fire-proof self-extinguishing class1 fire-reaction compliant washable, mechanically fixed to the frame

#### Muffler:

- Residential type, integrated in the canopy
- With high heat resistant paint coating

#### **Control Panel:**

- Self-standing control panel tower made with metal structure IP33
- Easy access to control panel through a canopy's door, equipped with lexan window
- Control panel is divided in two independent and insulated boxes separating Controls (Controller and numbered terminal board) from Power connection (circuit breaker and cable inlet)
- External dedicated area to make easier the electrical connection to the load
- Power connection between circuit breaker and alternator made with high resistance cables and using cable glands for waterproof connections

All units and components are prototype tested, factory build and production tested. A specific control procedure during the several stages of production ensures long life and reliability.

#### Data reference

Standard reference conditions temperature 25°C, altitude 1-1000m asl, relative humidity 30%, atmospheric pressure 100 kPa (1 bar), power factor 0.8 lag, balanced load - non distortional. Fuel consumption is nominal and refers to specific weight 0.850 gr/lt. Power performance data as quoted can be obtained after the initial running-in period of the engine, during which one has to follow the instructions of the engine manufacturer as stated in the use and maintenance manual of the specific engine. The tolerance shown by the engine manufacturer is +/- 5%. Sound power values refer to free field conditions: the installation site may influence the values. Dimensions, weights and other specifications contained in the technical data sheet and related attachments are nominal, subject to tolerances and refer to the model with standard equipment; any optional and additional equipment/accessories can modify weight, dimensions, performance.P.R.P. Prime Power-Continuous power at variable load: The power that a genset can supply in continuous service at a variable load for an unlimited applicable overload must be less than the percentages stated by the Manufacturer.L.T.P. Limited-time running power-Limited power: The maximum power that a genset can supply for a limited time respecting the maintenance intervals established in the environmental conditions stated by the Manufacturer according to ISO 8528-1. The number of hours per year is stated by the Manufacturer. Overload is not permitted. For reasons of transport and/or storage, liquids (oil and antifreeze) and batteries might not be included in the delivery.





# **DIAMOND RGU375PS**

60Hz@1800RPM 440/254V 3PH



#### **Engine general data**

Perkins
1506A-E88TAG5
312.00
345.00
Diesel
6
Turbocharged
Water
8.80
Electronic
G2 - 0.25
-
-
-
24

#### Alternator general data

Alternator brand	Stamford
Model	S4L1D-E
Type of excitation	Self-excited
Type of regulation	AVR
Regulator precision +/-%	1.00

## Structure data

Type of structure	DIAMOND
Tank capacity I.	500
Retention basin	yes
Exhaust diameter mm	-

## **Fuel consumption**

Consumption 25% I./h	0.00
Consumption 50% I./h	38.90
Consumption 75% I./h	56.80
Consumption 100% I./h	77.10
Autonomy at 75% of load h.	≈ 9 h

## **Engine liquids and equipment**

Type of lubricant	Oil SAE 15W40
Lubrication capacity I.*	41.00
Type of coolant	Antifreeze liquid
Coolant capacity I.*	33.20
Air intake filter	Paper cartridge
Battery capacity Ah	120
Number of batteries*	2

### Fuel system and energy balance

AC pump suction head kPa	6
Combustion air flow volume LTP m3/min	23.60
Cooling air capacity LTP m3/min	482.00
Exhaust gas flow-density LTP m3/min	59.60
Exhaust gas temperature LTP °C	512.00
Brake mean effective pressure kPa	10.00
Energy to exhaust LTP kWt	259.00
Energy to coolant LTP kWt	224.00
Energy to radiation LTP kWt	16.00

### **Control panel features**

### QTVA-7320

Self-standing tower with metal box

Circuit breaker

AMF controller DSE7320

- Voltmeter, Frequencymeter, Ammeter
   Generator power (kW, kV Ar, kV A & pf) monitoring
- Hour meter
- Fuel level meter
- Overload (kW & kV Ar) protection
- Low oil pressure protection
- High coolant temperature protection
- Low fuel level protection
- Battery charger alternator fault

- Rpm protection Emergency stop button Audible alarm

Terminal board for ATS connection

RS232 & RS485 Port

Can Bus reading Port (if standard on the engine)

Battery charger

On/off switch



Dealer



