

# DUPLEX GU25KO

60Hz@1800RPM 240/138V 3PH

**GENMAC**  
POWER PRODUCTS

KOHLER. 

## General features



Picture for illustration purposes only

Open generator with following specifications:

### Frame:

- Heavy duty fabricated welded base plate with high quality steel UNI S235 JR
- Heavy duty rubber anti-vibration mountings
- Fuel tank with drain plug
- Easy access to fuel refilling
- Feet and four lifting holes on the base

### Muffler:

- Industrial type
- With aluminum coating

### Control Panel:

- Metal Control panel with protective back cover
- Dedicated area to make easier the electrical connection to the load

All units and components are prototype tested, factory build and production tested. A specific control procedure during the several stages of production ensures long life and reliability.

## Overall performance

### GU25KO

PRP Continuous power kVA	21
PRP Continuous power kW	17
LTP Stand-by power kVA	23
LTP stand-by power kW	19
Power factor cos $\phi$	0.8
Voltage VAC	240/138
Frequency Hz	60
Ampere PRP/LTP	51 / 56
Speed RPM	1800

## Dimensions and noise level

Length mm	1400
Width mm	660
Height mm	1360
Net Weight kg	460
Gross Weight kg	-
Sound pressure at 7 mt dBA	-

## Data reference

Standard reference conditions temperature 25°C, altitude 1-1000m asl, relative humidity 30%, atmospheric pressure 100 kPa (1 bar), power factor 0.8 lag, balanced load - non distortional. Fuel consumption is nominal and refers to specific weight 0.850 gr/lt. Power performance data as quoted can be obtained after the initial running-in period of the engine, during which one has to follow the instructions of the engine manufacturer as stated in the use and maintenance manual of the specific engine. The tolerance shown by the engine manufacturer is +/- 5%. Sound power values refer to free field conditions: the installation site may influence the values. Dimensions, weights and other specifications contained in the technical data sheet and related attachments are nominal, subject to tolerances and refer to the model with standard equipment; any optional and additional equipment/accessories can modify weight, dimensions, performance.P.R.P. Prime Power-Continuous power at variable load: The power that a genset can supply in continuous service at a variable load for an unlimited number of hours per year while respecting the maintenance intervals established in the environmental conditions stated by the Manufacturer. according to ISO8528-1. The average power supplied over time and any applicable overload must be less than the percentages stated by the Manufacturer.L.T.P. Limited-time running power-Limited power: The maximum power that a genset can supply for a limited time respecting the maintenance intervals established in the environmental conditions stated by the Manufacturer according to ISO 8528-1.The number of hours per year is stated by the Manufacturer. Overload is not permitted.\*For reasons of transport and/or storage, liquids (oil and antifreeze) and batteries might not be included in the delivery.

**GENMAC**  
POWER PRODUCTS



# DUPLEX GU25KO

60Hz@1800RPM 240/138V 3PH

**GENMAC**  
POWER PRODUCTS

## Engine general data

Engine brand	Kohler
Model	KDI1903M
PRP Power kW	19.10
LTP Power kW	21.00
Fuel	Diesel
Nr. cylinders	3
Air intake	Aspirated
Cooling	Water
Cubic capacity l.	1.86
Speed regulation	Mechanical
Performance Class - steady state regulator accuracy +/- %	G2 - 0.50
Load Step G1 - KWe	-
Load Step G2 - KWe	-
Load Step G3 - KWe	-
Voltage VDC	12
Emissions	EPA Tier 3

## Alternator general data

Alternator brand	Mecc-Alte
Model	ECP28-M/4C
Type of excitation	Self-excited
Type of regulation	AVR
Regulator precision +/- %	1.00

## Structure data

Type of structure	DUPLEX
Tank capacity l.	100
Retention basin	not
Exhaust diameter mm	45

## Control panel features

### QFIA-4520

Protection cover  
Circuit breaker  
AMF controller DSE4520  
- Voltmeter, Frequencymeter, Ammeter  
- Generator power (kW, kV Ar, kV A & pf) monitoring  
- Hour meter  
- Fuel level meter  
- Overload (kW & kV Ar) protection  
- Low oil pressure protection  
- High coolant temperature protection  
- Low fuel level protection  
- Battery charger alternator fault  
- Rpm protection  
Emergency stop button  
Terminal board for ATS connection  
Battery charger  
On/off switch

## Fuel consumption

Consumption 25% l./h	1.70
Consumption 50% l./h	2.80
Consumption 75% l./h	4.00
Consumption 100% l./h	5.20
Autonomy at 75% of load h.	≈ 25 h

## Engine liquids and equipment

Type of lubricant	Oil SAE 5W40 CH-4
Lubrication capacity l.*	8.90
Type of coolant	Antifreeze liquid
Coolant capacity l.*	6.80
Air intake filter	Paper cartridge
Battery capacity Ah	50
Number of batteries*	1

## Fuel system and energy balance

AC pump suction head kPa	1
Combustion air flow volume LTP m3/min	1.30
Cooling air capacity LTP m3/min	36.80
Exhaust gas flow-density LTP m3/min	4.70
Exhaust gas temperature LTP °C	550.00
Brake mean effective pressure kPa	6.00
Energy to exhaust LTP kWt	15.00
Energy to coolant LTP kWt	19.20
Energy to radiation LTP kWt	4.50



Dealer