EXTREME G1260PS

50Hz@1500RPM 400/230V 3PH









Picture for illustration purposes only

Overall performance	G1260PS
PRP Continuous power kVA	1253
PRP Continuous power kW	1002
LTP Stand-by power kVA	1350
LTP stand-by power kW	1080
Power factor cos fiq	0.8
Voltage VAC	400/230
Frequency Hz	50
Ampere PRP/LTP	1811 / 1951
Speed RPM	1500

Dimensions and noise level

Length mm	8600
Width mm	2200
Height mm	3400
Net Weight kg	14100
Gross Weight kg	-
Sound pressure at 7 mt dBA	73.00

General features

Silent generator with following specifications:

Frame:

- Heavy duty fabricated welded base plate with high quality steel UNI S235.JR
- Heavy duty, bell type, rubber anti-vibration mountings
- Fuel tank with drain plug and retention basin
- Oil draining mechanical pump

Canopy:

- Large doors for easy access for service and monitoring (maintenance)
 Electro-galvanized sheet DC01+ZE25/25 (EN 10152: 2009)
- High precision sheet cutting with nitrogen laser technology to avoid
- Weatherproof sealed joints
- Nylon hinges
- Lockable handles in each door
 "Orange peel" specific powder coat paint for outdoor usage white **RAI 9010**
- Rain cap on exhaust outlet
- Coolant refilling specific hatch
 Fuel filler outside enclosure
- Ecological Sound foam: 100% Recyclable, 40mm thickness, fire-proof self-extinguishing class1 fire-reaction compliant washable, mechanically fixed to the roof with zinc plated metal supports and to the doors with metal grid

Muffler:

- Supersilent, Residential type
- With high heat paint coating

Control Panel:

- Self-standing control panel tower made with metal structure easily removable for maintenance
- Easy access to control panel through a canopy's door, equipped with lexan window
- Control panel is divided in two independent and insulated boxes separating Controls (Controller and numbered terminal board) from Power connection (circuit breaker and cable inlet)
- External dedicated area to make easier the electrical connection to the
- Power connection between circuit breaker and alternator made with high resistance cables and using cable glands for waterproof connections

All units and components are prototype tested, factory build and production tested. A specific control procedure during the several stages of production ensures long life and reliability.

Data reference

Standard reference conditions temperature 25°C, altitude 1-1000m asl, relative humidity 30%, atmospheric pressure 100 kPa (1 bar), power factor 0.8 lag, balanced load - non distortional. Fuel consumption is nominal and refers to specific weight 0.850 gr/lt. Power performance data as quoted can be obtained after the initial running-in period of the engine, during which one has to follow the instructions of the engine manufacturer as stated in the use and maintenance manual of the specific engine. The tolerance shown by the engine manufacturer is +/- 5%. Sound power values refer to free field conditions: the installation site may influence the values. Dimensions, weights and other specifications contained in the technical data sheet and related attachments are nominal, subject to tolerances and refer to the model with standard equipment; any optional and additional equipment/accessories can modify weight, dimensions, performance.P.R.P. Prime Power-Continuous power at variable load: The power that a genset can supply in continuous service at a variable load for an unlimited number of hours per year while respecting the maintenance intervals established in the environmental conditions stated by the Manufacturer. according to ISO8528-1. The average power supplied over time and any applicable overload must be less than the percentages stated by the Manufacturer.L.T.P. Limited-time running power-Limited power: The maximum power that a genset can supply for a limited time respecting the maintenance intervals established in the environmental conditions stated by the Manufacturer according to ISO 8528-1. The number of hours per year is stated by the Manufacturer. Overload is not permitted. For reasons of transport and/or storage, liquids (oil and antifreeze) and batteries might not be included in the delivery.





EXTREME G1260PS

50Hz@1500RPM 400/230V 3PH



Engine general data

Engine brand	Perkins
Model	4012-46TWG2A
PRP Power kW	1,055.00
LTP Power kW	1,166.00
Fuel	Diesel
Nr. cylinders	12
Air intake	Turbo intercooler
Cooling	Water
Cubic capacity I.	45.48
Speed regulation	Electronic
Performance Class - steady state regulator accuracy +/- %	0.25
Load Step G1 - KWe	-
Load Step G2 - KWe	-
Load Step G3 - KWe	-
Voltage VDC	24
Emissions	-

Alternator general data

Alternator brand	Mecc-Alte
Model	ECO43-2L/4A
Type of excitation	Self-excited
Type of regulation	AVR
Regulator precision +/-%	1.00

Structure data

Type of structure	EXTREME
Tank capacity I.	400
Retention basin	yes
Exhaust diameter mm	2

Fuel consumption

Consumption 25% I./h	-
Consumption 50% I./h	143.00
Consumption 75% I./h	196.00
Consumption 100% I./h	259.00
Autonomy at 75% of load h.	≈ 2 h

Engine liquids and equipment

Type of lubricant	Oil SAE 15W40
Lubrication capacity I.*	177.00
Type of coolant	Antifreeze liquid
Coolant capacity I.*	201.00
Air intake filter	Paper cartridge
Battery capacity Ah	50 Ah Optima
Number of batteries*	4

Fuel system and energy balance

AC pump suction head kPa	2
Combustion air flow volume LTP m3/min	109.00
Cooling air capacity LTP m3/min	1,680.00
Exhaust gas flow-density LTP m3/min	235.00
Exhaust gas temperature LTP °C	422.00
Brake mean effective pressure kPa	5.00
Energy to exhaust LTP kWt	1,009.00
Energy to coolant LTP kWt	637.00
Energy to radiation LTP kWt	89.00

Control panel features

QTVA-7320

Self-standing tower with metal box

Circuit breaker

AMF controller DSE7320

- Voltmeter, Frequencymeter, Ammeter
 Generator power (kW, kV Ar, kV A & pf) monitoring
- Hour meter
- Fuel level meter
- Overload (kW & kV Ar) protection
- Low oil pressure protection
- High coolant temperature protection
- Low fuel level protection
- Battery charger alternator fault

- Rpm protection Emergency stop button Audible alarm

Terminal board for ATS connection

RS232 & RS485 Port Can Bus reading Port (if standard on the engine)

Battery charger On/off switch



Dealer



