

BETA GU80DO

60Hz@1800RPM 380/220V 3PH

GENMAC
POWER PRODUCTS



STAMFORD



Picture for illustration purposes only

General features

Open generator with following specifications:

Frame:

- Heavy duty fabricated welded base plate with high quality steel UNI S235 JR
- Heavy duty, bell type, rubber anti-vibration mountings
- Fuel tank with drain plug and retention basin
- Dedicated area to make easier the electrical connection to the load
- Easy access to fuel refilling
- Feet and four lifting holes on the base

Muffler:

- Industrial type
- With aluminum coating

Control Panel:

- Self-standing control panel tower made with metal structure and components to grant IP65 protection, easily removable for maintenance
- Control panel is divided in two independent and insulated boxes separating Controls (Controller and numbered terminal board) from Power connection (circuit breaker and cable inlet)
- Dedicated area to make easier the electrical connection to the load
- Power connection between circuit breaker and alternator made with high resistance neoprene cables (H07RNF) and using cable glands for waterproof connections

All units and components are prototype tested, factory build and production tested. A specific control procedure during the several stages of production ensures long life and reliability.

Overall performance

GU80DO

PRP Continuous power kVA	60
PRP Continuous power kW	48
LTP Stand-by power kVA	66
LTP stand-by power kW	53
Power factor cos ϕ	0.8
Voltage VAC	380/220
Frequency Hz	60
Ampere PRP/LTP	91 / 101
Speed RPM	1800

Dimensions and noise level

Length mm	2250
Width mm	1020
Height mm	1521
Net Weight kg	850
Gross Weight kg	-
Sound pressure at 7 mt dBA	-

Data reference

Standard reference conditions temperature 25°C, altitude 1-1000m asl, relative humidity 30%, atmospheric pressure 100 kPa (1 bar), power factor 0.8 lag, balanced load - non distortional. Fuel consumption is nominal and refers to specific weight 0.850 gr/lt. Power performance data as quoted can be obtained after the initial running-in period of the engine, during which one has to follow the instructions of the engine manufacturer as stated in the use and maintenance manual of the specific engine. The tolerance shown by the engine manufacturer is +/- 5%. Sound power values refer to free field conditions: the installation site may influence the values. Dimensions, weights and other specifications contained in the technical data sheet and related attachments are nominal, subject to tolerances and refer to the model with standard equipment; any optional and additional equipment/accessories can modify weight, dimensions, performance.P.R.P. Prime Power-Continuous power at variable load: The power that a genset can supply in continuous service at a variable load for an unlimited number of hours per year while respecting the maintenance intervals established in the environmental conditions stated by the Manufacturer. according to ISO8528-1. The average power supplied over time and any applicable overload must be less than the percentages stated by the Manufacturer.L.T.P. Limited-time running power-Limited power: The maximum power that a genset can supply for a limited time respecting the maintenance intervals established in the environmental conditions stated by the Manufacturer according to ISO 8528-1.The number of hours per year is stated by the Manufacturer. Overload is not permitted.*For reasons of transport and/or storage, liquids (oil and antifreeze) and batteries might not be included in the delivery.



Engine general data

Engine brand	Deutz
Model	BF4M2011C
PRP Power kW	-
LTP Power kW	-
Fuel	Diesel
Nr. cylinders	4
Air intake	Turbo intercooler
Cooling	Oil
Cubic capacity l.	3.11
Speed regulation	Mechanical
Performance Class - steady state regulator accuracy +/- %	G2 - 5.00
Load Step G1 - KWe	-
Load Step G2 - KWe	-
Load Step G3 - KWe	-
Voltage VDC	12
Emissions	-

Alternator general data

Alternator brand	Stamford
Model	S1L2-Y1
Type of excitation	Self-excited
Type of regulation	AVR
Regulator precision +/- %	1.00

Structure data

Type of structure	BETA
Tank capacity l.	150
Retention basin	yes
Exhaust diameter mm	120

Control panel features

QT2A-4520

Self-standing tower with IP65 metal box
 Circuit breaker
 AMF controller DSE4520
 - Voltmeter, Frequncymeter, Ammeter
 - Generator power (kW, kV Ar, kV A & pf) monitoring
 - Hour meter
 - Fuel level meter
 - Overload (kW & kV Ar) protection
 - Low oil pressure protection
 - High coolant temperature protection
 - Low fuel level protection
 - Battery charger alternator fault
 - Rpm protection
 Emergency stop button
 Audible alarm
 Terminal board for ATS connection
 Can Bus reading Port (if standard on the engine)
 Battery charger
 On/off switch

Fuel consumption

Consumption 25% l./h	4.13
Consumption 50% l./h	7.40
Consumption 75% l./h	11.11
Consumption 100% l./h	15.10
Autonomy at 75% of load h.	≈ 14 h

Engine liquids and equipment

Type of lubricant	Oil SAE 15W40
Lubrication capacity l.*	13.00
Type of coolant	-
Coolant capacity l.*	-
Air intake filter	Paper cartridge
Battery capacity Ah	70
Number of batteries*	1

Fuel system and energy balance

AC pump suction head kPa	3
Combustion air flow volume LTP m3/min	-
Cooling air capacity LTP m3/min	-
Exhaust gas flow-density LTP m3/min	-
Exhaust gas temperature LTP °C	-
Brake mean effective pressure kPa	3.00
Energy to exhaust LTP kWt	-
Energy to coolant LTP kWt	-
Energy to radiation LTP kWt	-



Dealer